



## △-FIRE

### 4 zone fire panel

### CROSSFIRE 4K

#### SALIDAS (INCENDIO)

Siren outputs with resettable fuse	<b>2</b>
Fault relay	<b>1</b>
Alarm relay	<b>1</b>
Individual outputs by zone	<b>Yes</b>
Error and omission outputs	<b>Yes</b>
Remote outputs with relay	<b>Yes, with the RM4 module</b>

#### PROGRAMACIÓN

Day / night mode	<b>Yes</b>
Zone mapping for exits	<b>Yes</b>
Cross detection function	<b>Yes</b>
Levels	<b>3 (Useful / Very Useful / Installer)</b>
Test zone / Omission / Evacuation Mode	<b>Yes</b>

#### ZONAS (INCENDIO)

Maximum number of zones	<b>4</b>
Maximum number of detectors per zone	<b>30</b>

#### GENERAL INFORMATION

Technology	<b>Convencional</b>
Type of Central	<b>Incendio</b>

#### CERTIFICATION

Normative	<b>EN54-2 / EN54-4</b>
CPR	<b>Yes</b>

#### MATERIAL AND DIMENSIONS

Dimensions	<b>321 x 286 x 90 mm</b>
------------	--------------------------