



HIKVISION
accessories

Reader indoor with fingerprint /
card mifare 13.56mhz

DS-K1201AMF

IDENTIFICATION

Mode	Fingerprint / Card
Number of fingerprints	5000
Type of card	MIFARE 13.56MHz
Maximum reading distance	3 cm ~ 10 cm
Tiempo de reconocimiento huella	inferior a 1 s
Fingerprint sensor type	Optical Sensor
False positive ratio (FAR) fingerprint	≤ 0.001%
Negative false ratio (FRR) fingerprint	≤ 0.01%
Multi-factor authentication	Yes

POWER CONSUMPTION

Power mode	DC
Voltage	12V
Consumption (w)	1.6W

FEATURES

Sound warning	Yes
Tamper	Sí
DIP Switch	Yes

COMMUNICATION

Communication mode to the controller	RS485
--------------------------------------	--------------

MATERIAL AND DIMENSIONS

Installation	Surface
Dimensions	132 x 62 x 44 mm
Net weight	260 g
Weight with packaging	420 g

AMBIENT

Operating temperature	-40 °C ~ 70 °C
Use	Indoor
Maximum humidity	90%

GENERAL INFORMATION

Control type	Reader
--------------	---------------

